



## Four Port Audio Combiner

### Key Features

- Combines four Audio paths to a single connection
- Four wire operation
- Both-way monitor option
- Passes line signaling
- Logic or keytone signaling
- Power and TX indicators
- Small size



### In Brief

The four port audio combiner combines four ports of audio. It has a total of four 600ohm four wire balanced line inputs which are internally combined to provide a common 600 ohm four wire balanced output; likewise signals into the common port are split across the four other ports.

Levels can be set for line input and output on each port independently allowing the engineer to compensate for individual line losses and to set the system up for balanced levels.

*In the interests of continued development, AWCSL reserve the right to change this specification without notice.*

### **A. W. Communication Systems Ltd**

Crook Barn  
The Crook  
Roweltown  
Carlisle, Cumbria CA6 6LH

Telephone +44(0) 1697 748777  
Fax +44(0) 1697 748778  
email sales@awcsl.com  
Website www.awcsl.com





## Dimensions

The unit measure 220mm wide by 230mm deep and 35mm high. It comes complete with one of our standard 12 volt power supplies.

The unit is mounted in a smart desktop ABS case.

## External Connectors

Power connector  
Main Port - RJ45  
Qty 4 Auxillary ports - RJ45

## Indicators

Power on LED  
Transmit LED

## Level Setting

The level to line is adjustable by use of the internal potentiometers. The adjustment range is +2dBm to – 20dBm line input and line output.

Ex factory, the line levels are set to the default standard of –10dBm.

*In the interests of continued development, AWCSL reserve the right to change this specification without notice.*

### A. W. Communication Systems Ltd

Crook Barn  
The Crook  
Roweltown  
Carlisle, Cumbria CA6 6LH

Telephone +44(0) 1697 748777  
Fax +44(0) 1697 748778  
email sales@awcsl.com  
Website www.awcsl.com

